

Access units
MOTION 868 MHz range

GOSwitch · GOKey GOPush · GOButton

Wall-mounted 868 MHz
Transmitters

Applicable to doors
roller · folding · sliding · swing · sectional
guillotine · fast · glass · revolving · barriers



The range of 868 MHz radio transmitters for built-in and surface-mounted wall installation also offers the possibility of being programmable in its PRO version, thus making the control of registering new receivers easier and providing greater installation control.



GOSwitch-S/E · GOSwitch-S/E Pro
GOKey-S/E · GOKey-S/E Pro
GOPush · GOButton Pro

Versatility

- Just one transmitter can open many different doors.
- Deadman and Alternative Operations.

Great security

- High security rolling code system with more keying bits.

Installer personalisation

- The installer can personalise the transmitter using the installer code and ASSISTANT and PROG-MAN programming tools for PRO versions. Non-PRO versions can use the MAESTRO transmitter.





Flexibility and speed when programming

- The transmitters and proximity equipment are programmed by radio without mechanical contact.
- The transmitter must be registered in the receiver like any other control.

Simplified community installation management

The following is available with the ASSISTANT programming tool:

- Database with all equipment, transmitters and proximity cards/tags provided in each installation.
- Possibility of assigning standby codes. Functional transmitters, cards and tags can be sold without having to visit the installation.
- Stolen or lost transmitters, cards and tags can be replaced by new, functional ones without having to visit the installation.
- Registrations via PIN, 1 4-digit code can be allocated to a receiver and all transmitters/proximity elements must have the same PIN to be programmed in the equipment. 2 PIN codes per transmitter is permitted. Also available with the PROGMAN portable programming tool.
- Possibility of personalizing devices with the installer code.
- Configuration of equipment parameters such as forbidding the radio and manual programming of devices.

TRANSMITTERS	
 <p>GOKey-S/E</p> <ul style="list-style-type: none"> • 868 MHz, 4-channel radio keypad. • Maximum range of 30 metres. • 4 activation codes, one per channel. • Code length from 1 to 8 digits. • Codes retained even during power cuts. • Power: 2 x 1.5V AAA batteries • Operating consumption: 12 mA • Battery lasts for approximately 2 years. • Keypad with battery saving function. • Light operating indicator for low battery and signal transmission. • Vandalproof screws. • Surface-mounted(S) or built-in(E). • Watertightness: IP43. • Size: 75 x 75 x 65 mm (diameter 58 mm on built-in version). 	 <p>GOSwitch-S/E</p> <ul style="list-style-type: none"> • 868 MHz, 2-channel dead-man radio key switch. • Two-position left-right switch with no lock. • Dead-man receivers will operate like a normal transmitter. • Maximum range of 30 metres. • Power supply: 1 x 3Vdc CR2032 type. • Operating consumption: 12mA. • Battery lasts for approximately 2 years • Vandalproof screws. • Surface-mounted(S) or built-in(E). • Watertightness: IP43. • Size: 75 x 75 x 65 mm (diameter 58 mm on built-in version).
 <p>GOPush</p> <ul style="list-style-type: none"> • 868 MHz, 2 or 4-channel radio button. • Maximum range of 30 metres. • Power: R 2032 3V. • Consumption: 12mA • Battery lasts for approximately 2 years. • Vandalproof screws. • Surface-mounted(S) or built-in(E). • Watertightness: IP55 • Size: 77 x 70 x 50 mm 	 <p>GOButton</p> <ul style="list-style-type: none"> • 868 MHz, 2-channel dead-man radio button. • Button pad with two open and close (deadman) buttons for wireless communications with the control panel. • Maximum range of 30 metres. • Power: R 2032 3V. • Consumption: 12mA • Battery lasts for approximately 2 years. • Vandalproof screws. • Light operating indicator for low battery and signal transmission. • Surface-mounted(S) or built-in(E). • Watertightness: IP20 • Size: 87 x 75 x 14 mm

RECEIVERS
Receivers MOTION. BASE, WAVE, STICK, CONNECT, ACCESS500, ACCESS1000, and control panels with built-in receivers.